

TECHNICAL BULLETIN



Date: 4th January 1995
 Ref: TB33
 Raised By: TC
 Distributed to: General

Rev.11th February 99

FADER PART NOS. USED IN SOUNDTRACS MIXERS

PREFIX ALL NUMBERS WITH POT00 (e.g. Jade channel fader = POT000070). For conventional rotary volume and gain controls see circuit diagrams or PCB parts lists. Some mixers are supplied optionally fitted with P&G faders. These are not listed here.

MODEL	CHAN	GRP	MAST	OTHER
16/8/16	0070	0070	0070	
CM/CMX	0070	0070	0073	0073 (CR level)
CP6800	0070	0070	0073	0073 (CR level)
DPC 2	0133	0133	0133	
FM/FME/X	0070	0070	0070	0073 (stereo)
FMB	0103	-	0073	0103 (stereo & telco ch)
INLINE	0070	-	0070	0073 (stereo ch)
JADE	0070	-	0073	0073 (stereo & FX ch) 0126 (monitor)
JADE-S				
vca	0070	-	0073	0126 (monitor)
m/fader	0133	0135	0073	0126 (monitor)
MEGAS				
Mix	0070	0070	0070	0073 (stereo ch)
Studio 0070	0070	0070	0073	(stereo ch)
Stage 1&2	0070	0070	0070	0073 (stereo ch) 0145 (FX return)
Mon 1&2	0136	0070	0070	
MC/MCX	0051*	0070	0070	
MR/MRX	0070	0070	0070	
MXD	0135	0135	0135	0150 (60mm FX) 0144 (stereo ch + FX)
PC MIDI	0070	-	0070	
QUARTZ	0070	-	0073	
S series	0051*	0051*	0051*	
SEQUEL	0070	0070	0070	0073 (stereo ch)
SEQUEL 2	0103	0103	0070	0137 (FX return)
SOLITAIRE				
vca	0070	-	0073	0136 (monitor)
m/fader	0133	-	0073	0136 (monitor)SOLO

TB33 – Page 2

FADERS IN SOUNDTRACS MIXERS page 2

MODEL	CHAN	GRP	MAST	OTHER
SOLO				
Live	0114	0114	0114	
Live 8	0138	0138	0138	0137 (stereo FX)
Logic	0138	0138	0138	
Midi	0138	0138	0138	
Monitor	0136	0136	0136	
SPA	0103	0103	0073	
T series	0070	0070	0070	
TOPAZ				
Rec	0135	0135	0135	
Proj	0135	0135	0135	
Macro	0151	0151	0150	0150 (stereo ch)
12/14/24-4	0151	0151	0150	0150 (stereo ch)
Maxi	0135	0135	0144	0144 (stereo ch)
MXD	0135	0135	0135	0144 (stereo ch)
VIRTUA	0133		0133	

FADER TYPES Unless noted, all faders are 10 k ohm log law

P/N	MAKER	TYPE
0051	Nobel	small 60mm *
0070	Alps	large (K series) 100mm with guides **
0073	Alps	as 0070 but stereo **
0103	Alps	as 0070 but 10 Kohm VCA law **
0114	Panasonic	PCB side mount 100mm
0126	Panasonic	large style 60mm
0133	Panasonic	motorised fader 100mm log + servo track
0135	Panasonic	PCB back mount 100mm
0136	Panasonic	PCB back mount 60mm
0137	Panasonic	as 0136 but stereo 60mm
0138	Panasonic	as 0135 but different lever
0144	Panasonic	as 0135 but stereo
0145	Panasonic	as 0137 but different lever
0150	Panasonic	miniature PCB back mount 60mm stereo
0151	Panasonic	as 0150 but mono ϕ

* 0051 faders are no longer available, substitute by 0136 faders. However the knob is different and must be changed at the same time. On mixers this old it is recommended that all faders are changed in complete sets.

** Alps stopped production of the A series (chrome finish) during 1995 replacing it with the K series (brown paint finish). K series can be used to replace all older A series directly, with an extra length of cable in some applications. As the feel is different we suggest that these

**TECHNICAL
BULLETIN**



TB33 - Page 3

faders are changed in sets (i.e. all inputs or all groups or both masters etc.) There are a very few A series POT0070 and POT0103 left in stock (Feb '97), but no POT0073.

φ 0150 stereo can be used in place of 0151 as Topaz PCB's are designed to take both.