

Date: 19TH February 1997
Ref: TB58
Raised By: TC
Distributed to: General

KNOB PART NOS. USED IN SOUNDTRACS MIXERS

Soundtracs have used a wide variety of knobs. Use the following list to quickly find the correct type.

MODEL	GENERAL		FADER OTHER			
16/8/16	C	S				
CM/CMX	C	S	mini trim knob: C10			
CP6800	C	S	mini trim knob: C10			
FM /E /X /B /M	K	S				
INLINE	R	S				
JADE (early)	138	11	Mon:FDR	ADP:138	CR:280	
JADE (late)	428	11	Mon:FDR	ADP:150	CR:280	
JADE-S vca	428	11	Mon:FDR	ADP:150	CR:280	Auto:38
m/fader	428	COND	Mon:FDR	ADP:150	CR:280	Auto:38
MEGAS 1 (All)	M	TPZ				
MEGAS 2(early)	138	TPZ				
(late)	428	TPZ				
M -R/C/CX/RX	K	S	MC(X) fader: CS9			
PC MIDI	K	S				
QUARTZ	R	S				
S series	C	CS9				
SEQUEL	R	S				
SEQUEL 2 (early)	138	TPZ	ADP:138			
(late)	428	TPZ	ADP:150			
SOLITAIRE						
(early) vca/midi	138	TPZ	ADP:138	CR:280	Auto:38	
(late)	428	TPZ	ADP:150	CR:280	Auto:38	
(early) m/fader	138	COND	ADP:138	CR:280	Auto:38	
(late)	428	COND	ADP:150	CR:280	Auto:38	
SOLO Live 4	M	FDR				
Live 8	M	11				
Logic	M	TPZ	Auto:38			
Midi	M	TPZ				
Monitor	M	11				

TB58 - FADERS IN SOUNDTRACS MIXERS page 2

MODEL	GENERAL	FADER OTHER
SPA	R	S
T series	K	S
TOPAZ		
Rec	Z	TPZ
Proj	428	TPZ
Macro	428	MAC
12/14/24-4	428	MAC
Maxi	428	TPZ
VIRTUA	DA	COND phones:138

CIRCULAR KNOB TYPES

In colour code first letter(s) = body colour, second letter(s) = cap/pointer colour

KEY	P/N SERIES	NOTES
38	KNOB-38-COLLET (body) KNOB-38-CAP (cap)	Large programmer knob
138	KNOB-138-L/GRY (body) KNOB-864-RED/W etc. (cap)	This range has a line on the separate cap and no line on the grey body. Colour is defined by the cap
150	KNOB-S150-L/GRY (body) KNOB-MC150-BLK (cap)	Collet knob
280	KNOB-280-L/GRY (body) KNOB-T280-GREY (cap)	Large collet knob
428	KNOB-428-G/RED etc	-BLU is pastel blue ..-DBL is "dark" or bright blue This is 2 colour 1 piece item with coloured pointer. This range replaced the 138 series during 1995
C	KNOB-ROT-4MM (body) INS-C151-RED (cap)	This range has a separate cap and a black body. Colour is defined by the cap. May not look as original.
C10	KNOB-ROT-10mm (body) INS-C101-RED (cap)	mini collet 10mm diameter
DA	KNOB-DA150-006 KNOB-MC150-BLK etc. (cap)	Push on knob
K	KNOB-RED, KNOB-BLUE etc.	note: KNOB-GREY-PALE & KNOB-GREY-DARK
M	KNOB-M-G/R	This is 2 colour 1 piece item. Not used on M series!
R	KNOB-10x6, KNOB-10x4 etc.	Caps are separate: KNOB-100-B/W etc. See Technical Bulletin 59 for full details of family
Z	KNOB-Z-G/GRN etc.	This is pastel 2 colour 1 piece item only on Rec 8.

Cont/.....

FADER KNOB TYPES

In colour code first letter(s) = body colour, second letter(s) = Line/poInter colour

11	KNOB-11-G/B	These look same as TPZ knob but sit lower.
CS9	KNOB00020 (or 21 or 22)	20 = blk, 21 = wht, 22 = blu (small lever / very old mixer)
COND	KNOB-COND-B/W	Conductive plastic for touch sensitive motor faders
FDR	KNOB-FDR-B/W	These fit P&G style levers
MAC	KNOB-MAC-G/BLK	Small type for 4mm lever
S	KNOB-S-WHITE (-1 etc.)	Fader knobs. Ether plain or with number on front.
TPZ	KNOB-TPZ-GRY/B	These look same as 11 knob but sit higher off panel.

SEE PARTS LISTINGS FOR INDIVIDUAL KNOBS / COLOUR CHOICES